

An FIR filter acts on the input sequence given by

$$x[0:5] = [1 \quad -3 \quad 5 \quad -2 \quad 6 \quad 2]^T; \quad x[n] = 0 \text{ for } n < 0 \text{ and } n > 5$$

to produce the output sequence given by

$$y[0:10] = [2 \quad -3 \quad 0 \quad 10 \quad 23 \quad -27 \quad 61 \quad -51 \quad 54 \quad 14 \quad -2]^T$$

and  $y[n] = 0$  for  $n < 0$  and  $n > 10$ .

Without performing a convolution, determine the response of the filter to the input sequence  $\tilde{x}[\cdot]$  whose which equals zero except for

$$\tilde{x}[0:9] = [2 \quad -6 \quad 10 \quad -4 \quad 11 \quad 7 \quad -5 \quad 2 \quad -6 \quad -2]^T$$